




GIUNTI FILETTATI

Type	Type of connection	SAE Flare	NPT	PS [bar]	Dimensions [mm]		Weight [g]	Pieces per box
					L	CH		
U2-4	SAE Flare unions	1/4"	-	120	38	12	23	100
U2-6		3/8"	-		44	17	46	100
U2-8		1/2"	-		50	20	73	50
U2-10		5/8"	-		58	23	113	50
U2-12		3/4"	-		63	27	164	50
UR2-64	Reducing SAE Flare unions	1/4" x 3/8"	-		42	17	38	100
UR2-84		1/4" x 1/2"	-		45	20	58	50
UR2-86		3/8" x 1/2"	-		48	20	66	50
UR2-108		1/2" x 5/8"	-		54	23	98	50
U1-4B	SAE Flare - NPT unions	1/4"	1/4"		38,1	14	32	100
U1-6C		3/8"	3/8"		41,2	17	48	100
U1-8D		1/2"	1/2"		49,8	22	92	50
U1-12F		3/4"	3/4"		57,6	27	152	50
U1-16H		1"	1"		68	36	277	50
U1-4A	SAE Flare - NPT reducing unions	1/4"	1/8"		32,9	12	20	100
U1-6B		3/8"	1/4"		41,1	17	39	100
U1-8C		1/2"	3/8"		45,2	20	64	50
U1-10D		5/8"	1/2"		53,8	23	102	50



UNIONS

Type	Type of connection	SAE Flare		NPT	ODS		PS [bar]	Dimensions [mm]		Weight [g]	Pieces per box
		m	f		Ø [in]	Ø [mm]		L	CH		
UR3-4A	Male/Female SAE Flare reducing unions	1/4"	-	1/8"f	-	-	120	29	14	21	100
UR3-46		3/8"	1/4"	-	-	-		33	17	38	100
UR3-68		1/2"	3/8"	-	-	-		38	22	66	50
UR3-810		5/8"	1/2"	-	-	-		45	25	99	50
UR3-812		3/4"	1/2"	-	-	-		46,5	27	132	50
UR3-1012		3/4"	5/8"	-	-	-		49,5	30	157	50
UR3-64		1/4"	3/8"	-	-	-		33	22	49	100
UR3-84		1/4"	1/2"	-	-	-		36	25	66	50
UR3-86		3/8"	1/2"	-	-	-		39	25	74	50
UR3-108		1/2"	5/8"	-	-	-		44	30	127	50
UR3-128		1/2"	3/4"	-	-	-		45	34	140	50
R.SX	Cylinder adaptors	1/4"	20 – 14 left thread female			-		29	25	46	100
R.DX		1/4"	W 21,8 – 14 right thread female			-		29	27	52	100
US3-44	Male SAE Flare - solder unions	1/4"	-	-	1/4"	-		26,5	12	17	100
US3-4M8		1/4"	-	-	-	8		26,5	12	15	100
US3-66		3/8"	-	-	3/8"	-		33	17	40	100
US3-6M8		3/8"	-	-	-	8		33	17	45	100
US3-6M10		3/8"	-	-	-	10		33	17	39	100
US3-88		1/2"	-	-	1/2"	-		35	20	55	100
US3-8M12		1/2"	-	-	-	12		35	20	55	50
US3-1010		5/8"	-	-	5/8"	16		42	23	82	50
US3-12M18		3/4"	-	-	-	18		45,5	27	123	50

